



Thomas & Betts

***UL Listed to Meet New Requirements for
Fluorescent Fixtures and Ballasts!***

Sta-Kon[®]

Luminaire Disconnect





Sta-Kon®

Luminaire Disconnect

Protect Electricians Servicing Fluorescent Lights from Electrical Shock!

Count on Thomas & Betts to help you meet the latest standards and code updates! The Sta-Kon® Luminaire Disconnect is the first UL® listed, CSA certified device available to meet the UL standard for fluorescent light fixtures taking effect January 1, 2008.

Designed in accordance with NEC 410.73(G), CEC part I, rule 30-308(4), the disconnect consists of two mating halves. Simply connect the finger-safe female (line) side via wire connectors to the incoming power side of the circuit, and the male (load) side to the ballast. When disconnected, the device enables safe servicing of the fixture and ballast without exposure to dangerous electrical shock hazard.

The Sta-Kon® Luminaire Disconnect is available in bulk quantities for fixture and ballast manufacturers to meet the new UL standard, as well as in convenient kits for electricians to bring existing installed fluorescent lighting up to code.

Ideal for:

- Fluorescent lighting fixture and ballast OEMs
- Electricians servicing fluorescent light fixtures
- Maintenance personnel requiring an electrical disconnect

Specifications

Housing:	Polycarbonate
Contacts:	Tin-plated brass
Integral Leads:	Insulated 18 AWG solid copper
Max. Temp. Rating:	105° C
Flammability:	UL94-V2 (V0 available on request)
Electrical Rating:	4A, 600V
Standards:	UL® Listed, CSA Certified, NEC® 410.73(G) 2005 edition compliant

- Oversized electrical contacts improve conductivity and reduce temperature rise
- Integral wire leads ease installation — even with multiple wire sizes — and support connection to copper or aluminum wiring
- Fool-proof design enables mating halves of disconnect to be installed only one way, eliminating possible incorrect polarization
- Finger-safe line side prevents installer from touching hot contacts and enables safe servicing without disconnecting power



Luminaire Disconnect

Cat. Number	Description	Std. Pkg. Qty.	UPC Number
Bulk Packaging for OEMs			
LD2-D	2-Pole Luminaire Disconnect	500	786209-86971
LD3-D	3-Pole Luminaire Disconnect	500	786209-86972
Kits for Servicing Electricians (includes two male/line half and two female/load half of the luminaire disconnect polybagged with installation instructions)			
LD2	2-Pole Luminaire Disconnect Kit	20	786209-86975
LD3	3-Pole Luminaire Disconnect Kit	20	786209-86976

www.tnb.com

Thomas & Betts

Please ask your Thomas & Betts sales representative for a complete catalog of quality Thomas & Betts electrical products or visit us at www.tnb.com. For customer service, call 1-800-816-7809. For technical questions, call 1-888-862-3289.

Thomas & Betts Corporation
 Electrical Division
 8155 T&B Boulevard
 Memphis, TN 38125
 901-252-5000

Thomas & Betts Ltd.
 700 Thomas Avenue
 Iberville, Québec J2X 2M9
 450-347-5318