

PORTABLE CORD SELECTION TABLE

2 Conductors	Cord Type	SVO, SJO, SVT	SJ, SJO, SJT, SJTO			S, SO, ST, STO														
	Cord Type	#18	#18	#16	#14	#18	#16	#14	#12	#10	#8	#6	#4	#3	#2	#1	#1/0	#2/0	#3/0	#250
	Cord Dia. Approx.	.250	.306	.330	.365	.380	.400	.540	.615	.675	.810	.940	1.060	1.170	1.270	1.440	1.520	1.770	1.920	2.160

3 Conductors	Cord Type	SVO, SJO, SVT	SJ, SJO, SJT, SJTO			S, SO, ST, STO															
	Cord Type	#18	#18	#16	#14	#18	#16	#14	#12	#10	#8	#6	#4	#3	#2	#1	#1/0	#2/0	#3/0	#4/0	#250
	Cord Dia. Approx.	.255	.325	.350	.385	.390	.420	.565	.645	.710	.850	1.000	1.070	1.240	1.340	1.510	1.650	1.750	1.800	2.070	2.39

4 Conductors	Cord Type	SVO, SJO, SVT	SJ, SJO, SJT, SJTO			S, SO, ST, STO														
	Cord Type	#18	#18	#16	#14	#18	#16	#14	#12	#10	#8	#6	#4	#3	#2	#1	#1/0	#2/0	#3/0	#4/0
	Cord Dia. Approx.	.355	.385	.425	.420	.420	.450	.610	.700	.765	.970	1.100	1.270	1.340	1.480	1.580	1.780	1.930	2.070	2.260

5 Conductors	Cord Type	Cord Type S, SO, ST, STO						
	Cord Type	#18	#16	#14	#12	#10	#8	#6
	Cord Dia. Approx.	.500	.540	.695	.780	.830	1.060	1.180